

# Biometrika

## Fx3100

### Fingerprint Scanner (Match-on-Board)



## Technical specifications

Fx3100 is a new smart scanner capable of processing and recognizing fingerprints on board (Match-on-Board).

The PC connected to the scanner is not involved in the processing of biometric data: images and templates of the users are not transferred to the PC, thus increasing security and privacy. Thanks to its safe area, the Fx3100 can internally store templates, files and passwords and is able to perform cryptographic operations.

Fx3100 is the ideal solution for digital signature applications (biometrically enabled). The PC sends the documents to be signed to the scanner, along with the specified certificate to be used. Access to the private signature key is granted once the user has been authenticated by his/her fingerprint.

Fx3100 is the ideal solution also for Single sign-on (or "passwords bank") applications, as it can internally store (within its safe area), the passwords that have to be provided to third party applications once the user has been biometrically authenticated.

### Fingerprint Sensor

- Optical, high resolution (500 dpi)
- Sensing area: 17.8 x 25 mm
- Size: 75 x 65 x 125 mm (WxHxD)

### Match-on-Board

- Core ARM9 (200 MHz) + 16 MB RAM
- Identity verification in less than 1,5 sec
- Basic storage: 4 MB Flash

### Encryption

- Internal key generation (RSA 1024 bit)
- Digital signature (RSA)
- 128 bit Symmetric Encryption
- Challenge-Response
- PKCS#11 compliant

### Interface and development

- USB 2.0 HS interface
- Supported OS: Windows (XP, Vista, 7,8), Linux
- TWAIN support for image acquisition (for Windows system only)
- Smart Card reader (optional)
- Fx2000/Fx2100 compliant
- FxISO SDK, Passwordbank SDK



# Fx3100

## Desktop Fingerprint Scanner

---

### Fingerprint Sensor

The high resolution of the sensor and the very large sensing area significantly improve fingerprint recognition accuracy. Thanks to these (top of the market) features, false rejections due to incorrect finger placement are drastically reduced.

---

### Accuracy and Efficiency

Most of the match-on-board and match-on-card solutions available on the market function on slow CPU and are therefore vulnerable to inaccuracies compared to systems that match fingerprint images on a PC. The Fx3100 is equipped with a powerful microprocessor (RISC 32-bit, 200 MHz, core ARM9) and with 32 MB of RAM; this allows accurate on-board fingerprint matching to be performed in less than 1,5 second.

---

### Storage

Fx3100 is equipped with 4MB of flash memory, where it is possible to store numerical data (called templates) extracted from the users' fingerprints. It is also possible to save digital certificates (x509), passwords (single sign-on) and other user's files. Maximum capacity enables the onboard storage of up to 1500 templates.

---

### Encryption and Digital Signature

Fx3100 has several cryptographic capabilities. The communications between the scanner and the PC are encrypted (128 bit), by using a SSL-like protocol which negotiates session keys. The scanner can internally generate pairs of asymmetric keys (RSA) and export (in x509 format) the related certificate. Fx3100 can digitally sign (RSA) a document by using a private key (stored internally or on a smart card) once the key owner has been biometrically authenticated.

---

### Security and privacy

Fx3100 capacity for performing onboard biometric and cryptographic operations represents a substantial improvement in security. Such operation performed on a PC are vulnerable to attacks or interception. This feature of Fx3100 boost safety and privacy, as the biometric data never leaves the scanner (unless explicitly required by the user).

---

### Integration and development (SDK)

Fx3100 can be integrated in third party applications in two different ways:

**FxISO SDK:** The developer can either exploit the new match-on-board capabilities of Fx3100 or match fingerprint images on a PC (by using Fx3100 in Fx2100 compliant way).

**PasswordBank SDK:** Password Bank provides a safe way for storing pairs of usernames and passwords inside the Fx3100 scanner or inside a smart card This SDK enables the integration of the Password Bank functionalities in third party applications.

**Biometrika**

Via Respighi 13, 47841 Cattolica (RN) ITALY  
Phone +39 0541 833160 Fax +39 0541 833166  
[www.biometrika.it](http://www.biometrika.it)